The following port address information applies to KAYPRO 10, KAYPRO 2/84, KAYPRO 2X, KAYPRO 4/84, KAYPRO 4X, and KAYPRO ROBIE.

I/O PORT ADDRESSES

Use	Port# (hex)	Device	Function
Keyboard:			
	05	ZSIO 1 Chan. B	Keyboard data(R/W). Eight-bit data from keyboard.
	07	ZSIO 1 Chan. B	Keyboard control/status I/O.
Video:			
	1C	6545/6845 EA	CRT controller status/control I/O.
	1D	6545/6845 EA	CRT controller data I/O.
Parallel Printer: (output only)			
	18 - 1B	74 373	Parallel printer port (write only).
Serial Printer I/O:			
	08 - 0B	WD 1943 COM 8116	Baud rate for serial printer port.
	0C	ZSIO 2 Chan. A	Serial printer data I/O (RS-232C).
	0E	ZSIO 2 Chan. A	Serial printer control/status I/O.
Serial Data I/O:			
	00 - 03	WD 1943 COM 8116	Baud rate for serial data port (write only).
	04	ZSIO 1 Chan. A	Serial data port (RS-232C). Data I/O.
	06	ZSIO 1 Chan. A	Serial data port (RS-232C). Status/control I/O.